

### GAZELLE G9204 1000A Auto Range Digital Clamp Meter

The Gazelle G9204 1000A clamp meter can measure Hi current range, capable to AC/DC voltage, AC Current, resistance, capacitance, frequency and temperature. It's simple, one handed operation and optimized ergonomics and a large backlight display fulfils the need of a wide variety of test and measurement requirements.



- Multi function for AC-DC Voltage, AC current, Resistance, Diode, Continuity, Frequency, Temperature measurements
- 1000A full range overload protection for additional safety during measurement
- CAT II 600V / CAT III 300V safety rating with double insulation
- Includes Gazelle branded carrying case



Specifications		
Model	Range	Best Accuracy
AC Current (A)	400A/1000A	±(1.5%+5)
AC Voltage (V)	4V/40V/400V/600V	±(1.2%+5)
DC Voltage (V)	400mV/4V/40V/400V/600V	±(0.8%+1)
Resistance (Ω)	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ	±(1%+2)
Frequency (Hz)	10Hz~10MHz	±(0.1%+3)
Temperature (°C)	-40 °C~1000°C	±(2%+8)
Features		
Jaw Capacity	40mm	
Diode	√	
Continuity Buzzer	√	
Low Battery Indication	√	
LCD Backlight	√	
Input Impedance for DCV	Around 10MΩ	
Battery	9V Battery (6F22)	

#### Standard Accessories

- Operating Manual
- Test Lead
- Temperature Probe
- Carrying Case

