

G9411 Wall Scanner

G9400 Series

The Gazelle G9411 wall scanner enables you to detect electric wire, metal object, wooden beams accurately. The new and improved wall scanners are great tools for interior finish, renovation, furniture installation, flooring, pipe installation, and building construction.



- Maximum depth, ferrous metals: 100 mm
- Non-ferrous metals (copper): 80 mm
- Copper wire ($\geq 4 \text{ mm}^2$): 40 mm
- Wood: 20 mm/38 mm
- AC electric wire: 50 mm

Standard Accessories

- Operating Manual
- Battery

Specifications	Range
Detect Principle	Electro-magnetic induction
Detects	Wooden beam, metal object, electric wire
Metal-scan depth	100mm @iron pipe; 80mm @brass pipe
Stud-scan depth (wood)	38mm
AC Electric Wire Depth	50mm
Detect Accuracy	$\pm 15\text{mm}$ @28.5mm depth drywall
Notifications	Voice
Power	3.7V 300mAh Li-ion
Product Net Weight	112g
Product Size	135 x 60mm x 25mm